



LED Status	Sensor Status
off	power off
flicker	work properly
on	abnormal

CABLE #1	
COLOR	FUNCTION
BLUE	+24V
WHITE/BLUE	GND
WHITE/BROWN	RX
BROWN	TX

	Fx	Fy	Fz	Mx	My	Mz
<b>CAPACITY</b>	300N	300N	300N	60Nm	60Nm	60Nm
<b>OVERLOAD CAPACITY</b>	1500N	1500N	1500N	300Nm	300Nm	300Nm
PEAK-TO-PEAK NOISE = 6.6 X RMS NOISE (EFFECTIVE RESOLUTION) NOISE IS MEASURED AT SAMPLING RATE 500HZ						
<b>PEAK-TO-PEAK NOISE</b>	0.5N	0.5N	0.9N	0.03Nm	0.03Nm	0.02Nm
<b>EFFECTIVE RESOLUTION</b>	0.08N	0.08N	0.14N	0.005Nm	0.005Nm	0.003Nm

SPECIFICATIONS	
POWER SUPPLY (VDC)	+24
CROSSTALK (%F.S.)	1.5
NON-LINEARITY (%F.S.)	0.5
HYSTERESIS (%F.S.)	0.5
OPERATING TEMP. RANGE (°C)	-40 TO +90
MASS (KG) NOT INCLUDING ADAPTOR	0.41

**SUNRISE INSTRUMENTS**  
[www.srisensor.com](http://www.srisensor.com)

SIX AXIS CIRCULAR LOAD CELL  
D83MM, ETHERNET TCP/IP OUTPUT

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN MM	M4313S3E1	REV. 0.2
--	-----------	-------------